



Download Instructions

For the Omni-3200 & Omni-3210

The following table describes the procedure to perform a terminal initiated download of a specific application and terminal configuration from a VeriCentre download server.

Step	User Action	Terminal Display
1	Power cycle the terminal.	Copyright splash screen
2	Press Enter (↵) + 7 simultaneously to enter system mode.	System Password?
3	Enter system mode password (manufacturer's default is 1 [ALPHA] [ALPHA] 66831) and press Enter (↵).	System = VPV50US2* *may vary depending on terminal OS
4	Press Backspace (⌫) to clear memory on the terminal.	Memory Test Mem will be lost Press func if ok
5	Press Enter (↵).	Memory Test Memory -OK-
6	Hold Clear (⌫) until the terminal beeps.	System = VPV50US2* *may vary depending on terminal OS
7	Press 7 to edit the CONFIG.SYS file.	Edit Config.sys
8	Press Enter (↵).	Recall?
9	Input download parameters. <ul style="list-style-type: none"> • *ZP = <Download Phone Number> • *ZA = <Application ID> • *ZT = <Terminal ID> 	= 800.283.3413 = VSPR048 = DBA PHONE #

10	<ul style="list-style-type: none"> • *ZR = 3 (Baud Rate. 1=300, 2=1200, 3=2400) 	
	Press Clear (X) to return to system mode.	System = VPV50US2* *may vary depending on terminal OS
	11	Press 0.
12	Press * for partial download or press Enter (↵) for full download.	Dial Connected -----
<p>After connecting to the download PC, the terminal displays ----- and status indicator asterisks (**-----). Each asterisk represents a 10% increment of the download. Estimated download time is 25-30 minutes for a 2400 baud terminal depending upon the size of the application.</p> <p>Upon successful completion of the download the terminal will display Download Done. The terminal will then power cycle and run the downloaded application.</p>		